

ServeRAID-MR10M SAS/SATA Controller (Withdrawn) Product Guide (withdrawn product)

The ServeRAID-MR10M SAS/SATA Controller is a high performance PCIe RAID Controller for external direct-attached storage, including IBM System Storage EXP3000. This RAID adapter provides investment protection by supporting SAS and SATA hard drive configurations, and providing performance enhancements enabled by a standard battery. The battery enables cached data protection during unexpected power outages when the controller is operating in its higher performance, write back mode.

Figure 1 shows the ServeRAID-MR10M SAS/SATA Controller.



Figure 1. ServeRAID-MR10M SAS/SATA Controller

Did you know?

This adapter is a high-performance RAID controller offering external SAS ports and a wide range of RAID features, and is suitable for most System x servers.

Part number information

Table 1. Part number and feature code

Description	Part number	Feature code
ServeRAID MR10M SAS/SATA Controller	44E8825 43W4339*	3559

* Part number 43W4339 has been withdrawn

Specifications

The ServeRAID MR10M has the following specifications:

- MD2 form factor card (2U low-profile height)
- Two SFF-8088 SAS x4 external connectors
- PCI Express x8 host interface
- SAS Controller: LSI 1078e
- 3 Gbps per port data transfer rate
- Supports SAS 3 Gbps and SATA 2
- 256 MB cache
- Li-Ion battery backup
- Maximum stripe size: 1024 KB
- RAID levels : RAID 0, 1, 5, 6, 10, 50, and 60

Operating environment

The ServeRAID-MR10M SAS/SATA Controller is supported in the following environment:

- Temperature:
 - At 0 - 1000 m (0 - 3000 ft): 10 - 35° C (50 - 95° F)
 - At 1000 - 2100 m (3000 - 7000 ft): 10 - 32° C (50 - 90° F)
- Relative humidity: 20 - 80% (non-condensing)

Warranty

The ServeRAID-MR10M SAS/SATA Controller has a one-year limited warranty. When installed on a System x server, these cards assume your system's base warranty and any IBM ServicePac upgrade. Batteries are consumables and therefore are not covered under the warranty.

Supported servers

The ServeRAID-MR10M Controller is supported on the IBM System x servers listed in Table 2.

Table 2. Supported System x servers

		x3100 M3	x3200 M2	x3200 M3	x3250 M2	x3250 M3	x3350	x3400	x3400 M2	x3400 M3	x3455	x3500	x3500 M2	x3500 M3
ServeRAID-MR10M Controller	44E8825	N	Y	Y	Y	Y	Y	Y	Y	Y	N	Y	Y	Y

Table 2 (continued). Supported System x servers

	x3550	x3550 M2	x3550 M3	x3620 M3	x3630 M3	x3650	x3650 T	x3650 M2	x3650 M3	x3655	x3690 X5	x3755	x3755 M3	x3850 M2	x3950 M2	x3850 X5
ServeRAID-MR10M Controller	Y	Y	Y	N	N	Y	N	Y	Y	N	N	Y	N	Y	Y	N

See the IBM ServerProven website for the latest information about the adapters supported by each System x server type: <http://ibm.com/servers/eserver/serverproven/compat/us/>

Related publications

For more information refer to the following documents:

- *ServeRAID MR10M User's Guide*
<http://www.ibm.com/support/docview.wss?uid=psg1MIGR-5074105>
- ServeRAID software and drivers
<http://www.ibm.com/support/docview.wss?uid=psg1SERV-RAID>
- IBM Announcement Letter
US: <http://ibm.com/common/ssi/cgi-bin/ssialias?infotype=dd&subtype=ca&&htmlfid=897/ENUS107-594> EMEA: <http://ibm.com/common/ssi/cgi-bin/ssialias?infotype=dd&subtype=ca&&htmlfid=877/ENUSZG08-0660>

Related product families

Product families related to this document are the following:

- [RAID Adapters](#)

Notices

Lenovo may not offer the products, services, or features discussed in this document in all countries. Consult your local Lenovo representative for information on the products and services currently available in your area. Any reference to a Lenovo product, program, or service is not intended to state or imply that only that Lenovo product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any Lenovo intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any other product, program, or service. Lenovo may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

Lenovo (United States), Inc.
8001 Development Drive
Morrisville, NC 27560
U.S.A.
Attention: Lenovo Director of Licensing

LENOVO PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some jurisdictions do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. Lenovo may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

The products described in this document are not intended for use in implantation or other life support applications where malfunction may result in injury or death to persons. The information contained in this document does not affect or change Lenovo product specifications or warranties. Nothing in this document shall operate as an express or implied license or indemnity under the intellectual property rights of Lenovo or third parties. All information contained in this document was obtained in specific environments and is presented as an illustration. The result obtained in other operating environments may vary. Lenovo may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Any references in this publication to non-Lenovo Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this Lenovo product, and use of those Web sites is at your own risk. Any performance data contained herein was determined in a controlled environment. Therefore, the result obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

© Copyright Lenovo 2024. All rights reserved.

This document, TIPS0736, was created or updated on November 14, 2011.

Send us your comments in one of the following ways:

- Use the online Contact us review form found at:
<https://lenovopress.lenovo.com/TIPS0736>
- Send your comments in an e-mail to:
comments@lenovopress.com

This document is available online at <https://lenovopress.lenovo.com/TIPS0736>.

Trademarks

Lenovo and the Lenovo logo are trademarks or registered trademarks of Lenovo in the United States, other countries, or both. A current list of Lenovo trademarks is available on the Web at <https://www.lenovo.com/us/en/legal/copytrade/>.

The following terms are trademarks of Lenovo in the United States, other countries, or both:

Lenovo®

ServeRAID

ServerProven®

System x®

Other company, product, or service names may be trademarks or service marks of others.